

Transformadores para montaje en PCB-TABLAS

 Medidas en mm.
 Dimensiones in mm.

Potencia en VA del Transformador	Carrete Tipo	Sn cm ²	W1 mm	W2 mm	Sep	N	A	I+D-0.3	E	T	U	L	V1	V2	X	Y	∅
1.5	37 x 10	1	35	26.6	NO	10	10	17.4	18.7	27	25	25.5	4 x 5	23.5			0.8
1.5	37 x 10 c/sep.	1	35	26.6	SI	10	10	17.4	18.7	27	25	25.5	4 x 5	23.5	6.6	9.9	0.8
2.5	37 x 13	1.3	35	26.6	NO	13	13	17.4	18.7	27	25	26.2	4 x 5	23.5			0.8
2.5	37 x 13 c/sep.	1.3	35	26.6	SI	13	13	17.4	18.7	27	25	26.2	4 x 5	23.5	6.6	9.9	0.8
2.5	25 x 13	1.8	41.5	37	NO	13.3	13.5	17.8	20.2	27.5	28	30.4	5 x 5	24			0.8
2.5	25 x 13 c/sep.	1.8	41.5	37	SI	13.3	13.5	17.8	20.2	27.5	28	30.4	5 x 5	24	8	8.9	0.8
4.5	25 x 17	2.12	41.5	37	NO	13.3	17.5	17.8	20.2	27.5	28	34.5	5 x 5	24			0.8
4.5	25 x 17 c/sep.	2.12	41.5	37	SI	13.3	17.5	17.8	20.2	27.5	28	34.5	5 x 5	24	8	8.9	0.8
5	25 x 20	2.5	41.5	37	NO	13.3	20.5	17.8	20.2	27.5	28	37.5	5 x 5	24			0.8
5	25 x 20 c/sep.	2.5	41.5	37	SI	13.3	20.5	17.8	20.2	27.5	28	37.5	5 x 5	24	8	8.9	0.8
B	62 x 16	2.56	48	40	NO	16.8	18.8	21.1	23.5	31	30.4	34.3	5 x 5	27.5			0.8
B	62 x 16 c/sep.	2.56	48	40	SI	16.8	18.4	21.1	23.5	31	30.4	34.3	5 x 5	27.5	9.5	10.5	0.8
B	62 x 20	3.2	48	40	NO	16.8	20.5	21.1	23.5	31	30.4	38.5	5 x 5	27.5			0.8
B	62 x 20 c/sep.	3.2	48	40	SI	16.8	20.5	21.1	23.5	31	30.4	38.5	5 x 5	27.5	9.5	10.5	0.8
B	62 x 25	4	48	40	NO	16.5	25.5	21.1	23.5	31	30.4	43.5	5 x 5	27.5			0.8
B	62 x 25 c/sep.	4	48	40	SI	16.5	25.5	21.1	23.5	31	30.4	43.5	5 x 5	27.5	9.5	10.5	0.8
10	75 x 20	4	57	47.5	NO	19.5	20.5	25.5	28.4	35.5	37.8	42	8 x 5	32			0.8
10	75 x 20 c/sep.	4	57	47.5	SI	19.5	20.5	25.5	28.4	35.5	37.8	42	8 x 5	32	11.3	12.7	0.8
12	75 x 22	4.2	57	47.5	NO	19.5	22.5	25.5	28.4	35.5	37.8	44	8 x 5	32			0.8
12	75 x 22 c/sep.	4.2	57	47.5	SI	19.5	22.5	25.5	28.4	35.5	37.8	44	8 x 5	32	11.3	12.7	0.8
15	75 x 30	5.7	57	47.5	NO	19.5	30.5	25.5	28.4	35.5	37.8	52	8 x 5	32			0.8
15	75 x 30 c/sep.	5.7	57	47.5	SI	19.5	30.5	25.5	28.4	35.5	37.8	52	8 x 5	32	11.3	12.7	0.8

